



SECTION

16-1A

ALUMINUM COMPRESSION FITTINGS CABLE TO FLAT PAD



The cast electrical aluminum compression terminals for connecting aluminum cable bus to a flat pad have the crimping die sizes clearly marked for ease of installation. For pads other than parallel to the cable bus add the degree variation from parallel to the catalog No. (Example: for pad 45 deg. from parallel to cable run specify catalog 16-161C-45).



Note: For short barrel terminals add the suffix -SHB

ALUMINUM Type ACP

CATALOG NUMBER w/PAD SIZE	CABLE SIZE AWG or MCM MIN. MAX	ASCR SIZE AWG or MCM MIN. MAX	CONDUCTOR DIAMETER	DIMENSIONS		DIE REF.	PAD THICKNESS
				A	B		
16-123B	#2	#2	.292-.325	6 1/2	1 1/2	.640	1/4
16-124B	1/0	1/0	.355-.398	6 1/2	1 1/2	.840	5/16
16-124C	1/0	1/0	.355-.398	6 3/4	1 1/2	.840	5/16
16-125B	2/0	2/0	.414-.447	6 1/2	2	.840	5/16
16-125C	2/0	2/0	.414-.447	6 3/4	2	.840	5/16
16-128B	3/0	3/0	.464-.502	6 3/4	2	.840	5/16
16-128C	3/0	3/0	.464-.502	7	2	.840	5/16
16-129B	4/0	4/0	.522-.563	7 1/4	3 3/4	.840	5/16
16-129C	4/0	4/0	.522-.563	7 1/2	3 3/4	.840	5/16
16-130B	226.8-300	266.8(26/7)	.586-.642	7 3/4	3 3/4	.840	5/16
16-130C	226.8-300	266.8(26/7)	.586-.642	8	3 3/4	.840	5/16
16-134B	336.4(19)-350(37)	336.4(36/1)-336.4(18/1)	.666-.684	7 1/2	3 3/4	1.312	7/16
16-134C	336.4(19)-350(37)	336.4(36/1)-336.4(18/1)	.666-.684	8 3/4	3 3/4	1.312	5/16
16-139B	397.5(19)-400(37)	336.4(26/7)-397.5(18/1)	.721-.743	8 1/2	3 3/4	1.125	7/16
16-139C	397.5(19)-400(37)	336.4(26/7)-397.5(18/1)	.721-.743	8 5/8	3 3/4	1.312	5/16
16-144B	450(37)-500(37)	397.5(24/7)-477(18/1)	.772-.814	8 1/2	5	1.312	7/16
16-144C	450(37)-500(37)	397.5(24/7)-477(18/1)	.772-.814	8 1/2	5	1.312	5/16
16-146B	550(61)-556.5(37)	477(24/7)-477(30/7)	.846-.883	8	5	1.312	7/16
16-146C	550(61)-556.5(37)	477(24/7)-477(30/7)	.846-.883	10 1/4	5	1.312	5/16
16-148B	600(37)-650(91)	556.5(24/7)-556.5(30/7)	.879-.953	9 3/4	5 1/2	1.500	1/2
16-148C	600(37)-650(91)	556.5(24/7)-556.5(30/7)	.879-.953	10 1/2	5 1/2	1.500	7/16
16-152B	700(61)-795(61)	605(26/7)-636(30/19)	.964-1.028	11 1/2	6 1/4	1.843	5/8
16-152C	700(61)-795(61)	605(26/7)-636(30/19)	.964-1.028	11 1/2	6 1/4	1.843	1/2
16-152D	700(61)-795(61)	605(26/7)-636(30/19)	.964-1.028	12 1/8	6 1/2	1.843	5/8
16-158B	800(61)-817.5(61)	715.5(54/7)-715.5(30/19)	1.031-1.081	11 1/2	6 3/4	1.843	5/8
16-158C	800(61)-817.5(61)	715.5(54/7)-715.5(30/19)	1.031-1.081	11 1/8	6 3/4	1.843	1/2
16-158D	800(61)-817.5(61)	715.5(54/7)-715.5(30/19)	1.031-1.081	12 1/8	7	1.843	5/8
16-161B	900(37)-1000(61)	795(24/7)-874.5(54/7)	1.092-1.152	11 1/2	6 3/4	1.843	5/8
16-161C	900(37)-1000(61)	795(24/7)-874.5(54/7)	1.092-1.152	10 3/4	6 3/4	1.843	5/8
16-161D	900(37)-1000(61)	795(24/7)-874.5(54/7)	1.092-1.152	12 1/8	7	1.843	5/8
16-164B	1033.5(37)-1113(61)	900(54/7)-954(54/7)	1.162-1.216	11 1/2	7 1/4	2.125	3/4
16-164C	1033.5(37)-1113(61)	900(54/7)-954(54/7)	1.162-1.216	11 1/2	7 1/4	2.125	3/4
16-164D	1033.5(37)-1113(61)	900(54/7)-954(54/7)	1.162-1.216	12	7 3/8	2.125	3/4
16-165C	1200(91)-1272(61)	1033.5(54/7)-1113(54/19)	1.246-1.300	13 1/4	9 1/4	2.375	3/4
16-165D	1200(91)-1272(61)	1033.5(54/7)-1113(54/19)	1.246-1.300	14 1/2	9 3/8	2.375	3/4
16-167C	1400(91)-1510.5(61)	1272(45/7)-1351.5(54/19)	1.345-1.424	13 1/4	9 1/4	2.375	3/4
16-167D	1400(91)-1510.5(61)	1272(45/7)-1351.5(54/19)	1.345-1.424	14 1/2	9 3/8	2.375	3/4
16-168C	1590(61)-1700(127)	1351.3(54/19)-1510.5(54/19)	1.424-1.506	13 1/4	9 1/4	2.375	3/4
16-168D	1590(61)-1700(127)	1351.3(54/19)-1510.5(54/19)	1.424-1.506	14 1/2	9 3/8	2.375	3/4
16-169C	1750(127)	1570.5(54/19)-1590(54/19)	1.506-1.545	13 1/4	9 1/4	2.375	3/4
16-169D	1750(127)	1570.5(54/19)-1590(54/19)	1.506-1.545	14 1/2	9 3/8	2.375	3/4
16-170D	2000(91)(127)	1780(84/19)	1.602-1.659	15	9 1/4	2.937	7/8
16-171D		2156(84/19)	1.750-1.762	15	9 1/4	2.937	7/8
16-172D	2500(127)		1.824	15	9 1/4	2.937	7/8
16-173D	3000(127)		1.996	15	9 1/4	2.937	7/8
16-174D	3500(127)		2.160	15	9 1/4	2.937	7/8

To insure the long term service and reliability of compression connectors the use of filler compounds is essential. Additional filler should be used in any application where the connector is installed with the barrel in the upright position.